

```

10 'Digital Speech Basic Loader
20 MEMORY 41999
30 FOR i=42000 TO 42328
40 READ a$:v=VAL("&" + a$)
50 cs=cs+v:POKE i,v
60 NEXT i
70 IF cs<>41144 THEN PRINT"DATA ERROR - Check listing";CHR$(7):STOP
80 CALL 42000
90 CLS:PRINT"New commands loaded - you can now NEW    this loader program."
100 END
110 DATA C3,3A,A5,F3,E5,DD,E1,06,08,AF,CD,35,A4,CD,2F,A4,17,10,F7,DD,77,00
120 DATA DD,23,1B,7A,B3,20,EA,FB,C9,26,11,25,20,FD,C9,C5,06,F5,ED,60,CB,14
130 DATA C1,C9,F5,3E,C0,06,F6,ED,79,06,F4,F1,ED,79,06,F6,3E,80,ED,79,06,F4
140 DATA ED,49,06,F6,AF,ED,79,C9,CD,A7,BC,F3,3E,03,0E,00,CD,3E,A4,3E,07,0E
150 DATA 3D,CD,3E,A4,3E,02,0E,00,CD,3E,A4,C9,E5,D5,CD,5A,A4,D1,E1,06,08,CB
160 DATA 06,C5,DC,9B,A4,D4,A5,A4,E5,26,01,CD,31,A4,E1,C1,10,ED,23,1B,7A,B3
170 DATA 20,E5,CD,A7,BC,FB,C9,F5,3E,09,0E,09,CD,3E,A4,F1,C9,F5,3E,09,0E,00
180 DATA CD,3E,A4,F1,C9,FE,03,20,0E,DD,7E,00,E6,0F,32,9F,A4,DD,23,DD,23,18
190 DATA 08,FE,02,C0,3E,09,32,9F,A4,DD,5E,00,DD,56,01,DD,6E,02,DD,66,03,CD
200 DATA 74,A4,C9,DD,5E,00,DD,56,01,DD,6E,02,DD,66,03,FE,02,C0,06,F6,3E,10
210 DATA ED,79,E5,21,1A,A5,7E,B7,28,06,CD,5A,BB,23,18,F6,CD,18,BB,FE,0D,20
220 DATA F9,3E,E0,CD,5A,BB,E1,CD,13,A4,3E,08,CD,5A,BB,3E,E1,CD,5A,BB,CD,71
230 DATA BC,C9,50,72,65,73,73,20,45,4E,54,45,52,20,74,6F,20,73,74,61,72,74
240 DATA 20,72,65,63,6F,72,64,69,6E,67,3A,00,01,44,A5,21,59,A5,CD,D1,BC,C9
250 DATA 4C,A5,C3,AF,A4,C3,D9,A4,52,45,50,4C,41,D9,52,45,43,4F,52,C4,00

```