

```
10 ' -----
20 '                               DUMP
30 ' -----
40 MODE 1
50 INK 1,1:INK 0,24
60 BORDER 1: PAPER 1 : PEN 0
70 CLS
80 INPUT "Adresse de debut (Hexa) ";DEB$
90 GOSUB 560
100 IF B$="N" THEN GOTO 80
110 DEB=NN
120 INPUT "Adresse de fin (Hexa) ";FIN$
```

```

130 GOSUB 570
140 IF B$="N" THEN GOTO 120
150 FIN = NN
160 IF DEB > FIN THEN PRINT "Adresse de
debut > Adresse de fin": GOTO 80
170 PRINT "Listage sur imprimante ?(O/N)
";
180 PRI$=INKEY$:IF PRI$="" THEN GOTO 180
190 IF PRI$<>"O" AND PRI$<>"o" AND PRI$<
>"N" AND PRI$<>"n" THEN GOTO 180
200 PRINT " ";PRI$
210 PRINT "Affichage 40 ou 80 Colonnes ?
"
220 PRINT "Repondre 1 pour 40 ; 2 pour 8
0"
230 A$=INKEY$:IF A$="" THEN GOTO 230
240 IF A$="1" THEN MODE 1: COL=8: GOTO 2
70
250 IF A$="2" THEN MODE 2:PAPER 1:PEN 2:
COL=16:GOTO 270
260 GOTO 220
270 CLS
280 L=1
290 FOR D=DEB TO FIN STEP COL
300 ON LEN(HEX$(D)) GOSUB 720,730,740,75
0
310 P0$=P0$+HEX$(D)+" "
320 PRINT P0$;:C1=6
330 IF COL=8 THEN C2=31 ELSE C2=55
340 FOR I=D TO D+COL-1
350 IF I> 65535 THEN GOTO 470
360 A=(PEEK(I))
370 A$=HEX$(A)
380 LOCATE C1,L
390 IF LEN(A$) = 1 THEN P$="O"+A$+" " EL
SE P$= A$+" "
400 PRINT P$
410 P1$=P1$+P$
420 LOCATE C2,L
430 IF A>31 AND A<127 THEN P$=CHR$(A) E
LSE P$= "."
440 PRINT P$
450 P2$=P2$+P$
460 C2=C2+1 : C1=C1+3
470 NEXT I
480 GOSUB 800
490 P0$="":P1$="":P2$=""
500 L=L+1
510 A$=INKEY$
520 IF L=24 THEN A$=INKEY$:IF A$="" THEN
GOTO 520 ELSE L=1 : CLS ELSE BB=1
530 NEXT D
540 IF L<>0 THEN GOSUB 800
550 END
560 DD$=DEB$: GOTO 580
570 DD$=FIN$: GOTO 580
580 NN=0
590 IF LEN(DD$)<>4 THEN B$="N": GOSUB 76
0: RETURN
600 FOR I=1 TO 4
610 V=ASC(MID$(DD$,I,1))
620 IF V > 64 AND V < 71 THEN N=V-55: ON
I GOTO 660,670,680,690

```

```

630 IF V > 47 AND V < 58 THEN N=V-48: ON
  I GOTO 660,670,680,690
640 GOSUB 760
650 B$="N" : RETURN
660 NN=NN+N*4096: GOTO 700
670 NN=NN+N*256: GOTO 700
680 NN=NN+N*16: GOTO 700
690 NN=NN+N
700 NEXT I
710 B$="O": RETURN
720 P0$="0"
730 P0$=P0$+"0"
740 P0$=P0$+"0"
750 RETURN
760 PRINT "Donner l'adresse sur 4 caract
eres HEXA": RETURN
770 '
780 '--- EDITION SUR IMPRIMANTE ---
790 '
800 IF PRI$="0" OR PRI$="o" THEN PRINT #
  8,P0$;P1$;P2$
810 RETURN

```