

```

A183 2821      1480      JR      Z,ERR01
A185 302E      1690      JR      NC,ERR04
A187 18E9      1700      JR      TRABA
A189 3A5CA2    1710      ERROS:  LD      A,(FLAG)
A18C FE01      1720      CP      1

Hisoft GENA3.1 Assembler. Page      4.

A18E 2009      1730      JR      NZ,PASE1
A190 210DA2    1740      LD      HL,TXT1
A193 CDB8A1    1750      CALL   P_ERR0
A194 CD18BB    1760      CALL   WKKEY
A199 CDBFBC    1770      PASE1:  CALL   #BC8F
A19C 2808      1780      JR      Z,ERR01
A19E 300B      1790      JR      NC,ERR02
A1A0 C07ABC    1800      CALL   #BC7A
A1A3 300B      1810      JR      NC,ERR03
A1A5 C9        1820      RET
A1A6 21C7A1    1830      ERR01:  LD      HL,XTXP2
A1A9 180D      1840      JR      P_ERR0
A1AB 21C7A1    1850      ERR02:  LD      HL,XTXP2
A1AE 1808      1860      JR      P_ERR0
A1B0 21C7A1    1870      ERR03:  LD      HL,XTXP2
A1B3 1803      1880      JR      P_ERR0
A1B5 21C7A1    1890      ERR04:  LD      HL,XTXP2
A1B8 E5        1900      P_ERR0:  PUSH   HL
A1B9 CD6CBB    1910      CALL   CLS
A1BC E1        1920      POP     HL
A1BD 46        1930      LD      B,(HL)
A1BE 23        1940      INC     HL
A1BF 7E        1950      P_ERR1:  LD      A,(HL)
A1C0 23        1960      INC     HL
A1C1 CD5ABB    1970      CALL   #BB5A
A1C4 18F9      1980      DJNZ   P_ERR1
A1C6 C9        1990      RET
A1C7 05        2000      TXP2P2:  DEFB   5
A1C8 4552524F  2010      DEFM   "ERROR"
A1CD          2020      NAMES:  DEFS   17
A1DE          2030      NAMES:  DEFS   17
A1EF 0E        2040      TXT1:   DEFB   14
A1F0 4E4F4D42  2050
      DEFM   "NOMBRE (LOAD):"
A1FE 0E        2060      TXTS:   DEFB   14
A1FF 4E4F4D42  2070
      DEFM   "NOMBRE (SAVE):"
A20D 27        2080      TXT1:   DEFB   39
A20E 494E5345  2090      DEFM   "INSERTA
DISCO DESTINO Y PULSA UNA TECLA"
A235 26        2100      TXT2:   DEFB   38
A236 494E5345  2110      DEFM   "INSERTA

```

Hi soft GENA3.1 Assembler. Page 1.

Pass 1 errors: 00

```

0000      10      ORG      #A000
BC0E      20      MODE:   EQU      #BC0E
BC39      30      BORDER: EQU      #BC38
BC32      40      INKS:   EQU      #BC32
BB6C      50      CLS:    EQU      #BB6C
BB75      60      COORD:  EQU      #BB75
BB5A      70      IMPRI:  EQU      #BB5A
BB18      80      WKEY:   EQU      #BB18
A000      90      CALL    #BB03
A003      100     CALL    CLS
A006      110     CALL    NAMEX
A009      120     CALL    INIC
A00C      130     RET
A00D      140     NAMEX:  LD        HL,TEXTL
A010      150     CALL    P_ERROR
A013      160     LD        HL,#1001
A016      170     CALL    INPUT
A019      180     LD        DE,NAMEX+1
A01C      190     CALL    TRASP
A01F      200     LD        A,(LONG)
A022      210     LD        (NAMEX),A
A025      220     CALL    BORRA
A028      230     CALL    CLS
A02B      240     LD        HL,TEXTS
A02E      250     CALL    P_ERROR
A031      260     LD        HL,#1001
A034      270     CALL    INPUT
A037      280     LD        DE,NAMEX+1
A03A      290     CALL    TRASP
A03D      300     LD        A,(LONG)
A040      310     LD        (NAMEX),A
A043      320     CALL    BORRA
A046      330     CALL    CLS
A049      340     RET
A04A      350     INPUT:  XOR      A
A04B      360     LD        (LONG),A
A04E      370     LD        DE,NAME
A051      380     CALL    COORD
A054      390     CALL    PAUSA
A057      400     LD        A,"-"
A059      410     CALL    IMPRI
A05C      420     I_BUC:  CALL    WKEY
A05F      430     LD        B,A
A060      440     CP        13
A062      450     RET
A063      460     CP        127
A065      470     JR        Z,DELETE
A067      480     CP        31
A069      490     JR        C,I_BUC
A06B      500     CP        123
A06D      510     JR        NC,I_BUC
A06F      520     LD        A,(LONG)
A072      530     CP        40
A074      540     JR        Z,I_BUC
A076      550     LD        A,8
A078      560     CALL    IMPRI

```

```

Hisoft  GENA3.1 Assembler. Page      3.

A101 2009      1150      JR      NZ,I_PASA
A103 210DA2    1160      LD      HL,TXT1
A106 CDB8A1    1170      CALL   P_ERROR
A109 C1C18BB   1180      CALL   WKLEY
A10C 21CDA1    1190      I_PASA: LD      HL,NAMES
A10F 46        1200      LD      B,(HL)
A110 23        1210      INC     HL
A111 119F51    1220      LD      DE,#519F
A114 CDBCB0    1230      CALL   #BC8C
A117 CAA6A1    1240      JP      Z,ERR01
A11A D2ABA1    1250      JP      NC,ERR02
A11D E5        1260      PUSH   HL
A11E 3A5DA2    1270      LD      A,(FLAGL)
A121 FE01      1280      CP      1
A123 2009      1290      JR      NZ,I_PAS1
A125 2135A2    1300      LD      HL,TXT2
A128 CDB8A1    1310      CALL   P_ERROR
A12B C1C18BB   1320      CALL   WKLEY
A12E 21DEA1    1330      I_PAS1: LD      HL,NAMEL
A131 46        1340      LD      B,(HL)
A132 23        1350      INC     HL
A133 119F31    1360      LD      DE,#319F
A136 C0778C    1370      CALL   #BC77
A139 2300      1380      JR      NZ,B1EN
A13B E1        1390      POP     HL
A13C 1868      1400      JR      ERRO1
A13E 3803      1410      B1EN:  JR      C,PASAR
A140 E1        1420      POP     HL
A141 186D      1430      JR      ERRO3
A143 E5        1440      PASAR: PUSH   HL
A144 DDE1      1450      POP     IX
A146 FDE1      1460      POP     IY
A148 DD7E12    1470      LD      A,(IX+18)
A148 FD7712    1480      LD      (IX+18),A
A14E DD7E15    1490      LD      A,(IX+21)
A151 FD7715    1500      LD      (IX+21),A
A154 DD7E16    1510      LD      A,(IX+22)
A157 FD7716    1520      LD      (IX+22),A
A15A DD7E18    1530      LD      A,(IX+24)
A15D FD7718    1540      LD      (IX+24),A
A160 DD7E19    1550      LD      A,(IX+25)
A163 FD7719    1560      LD      (IX+25),A
A166 DD7E1A    1570      LD      A,(IX+26)
A169 FD771A    1580      LD      (IX+26),A
A16C DD7E1B    1590      LD      A,(IX+27)
A16F FD771B    1600      LD      (IX+27),A
A172 CD89BC    1610      TRABA: CALL   #BC89
A175 282F      1620      JR      Z,ERR01
A177 3810      1630      JR      NC,ERR0S
A179 CD88BC    1640      CALL   #BC80
A17C 2828      1650      JR      Z,ERR01
A17E 3809      1660      JR      NC,ERR0S
A180 CD95BC    1670      CALL   #BC95

```

```

A25D                                2140 FLAGL:  DEFS 1
Pass 2 errors: 00

BIEN      A13E      BORDER BC38      BORR      A0CE
BORRA     A0C4      B_BUC  A0D3      CLS       BB6C
COORD     BB75      DELETE A090      ERROR1    A1A6
ERROR2    A1AB      ERROR3 A1B0      ERR04     A1B5
ERROS     A189      FLAG   A25C      FLAGL     A25D
IMPR1     BB5A      INIC   A0FC      INKS      BC32
INPUT     A04A      I_BUC  A05C      I_PAS1    A12E
I_PASA    A10C      LONG   A0EB      M0D0     BC0E
NAME      A0EC      NAME1  A1DE      NAMES     A1CD
NAMEX     A00D      PASAR   A143      PASE1     A199
PAUS      A0E5      PAUSA   A0E2      P_ERR1    A1BF
P_ERROR   A1B8      TRABA   A172      TRASP     A0D9
TXT1      A20D      TXT2    A235      TXTL      A1EF

Hisoft GENA3.1 Assembler. Page      5.

TXTP2     A1C7      TXT5     A1FE      WKEY      BB18

Table used:      506      from 1000

```

Hisoft GENA3.1 Assembler, Page 2.

```

A07B 78          570          LD  A,B
A07C CD5ABB      580          CALL IMPRI
A07E 3E5E        590          LD  A," "

```

Hisoft GENA3.1 Assembler. Page 5.

Table used: 506 from 1000