

PROGRAMA CARGARUT

```
10 LOAD "spectrum.bin",&A000
20 CALL &A000
30 CLS
40 PRINT "Rutinas de carga y salvad
o instaladas"
50 WHILE INKEY$("<")="":WEND
60 PRINT "pulsar una tecla"
70 WHILE INKEY$="":WEND
80 NEW
```

CARGADOR TRANSPAN

DIRECCION DE COMIENZO..9000

1 2108C0AF4FE60757790707E6,498

2 E05F790F0F0FE618B2F64057,522

3 0620E51AF5E6F07723F13600,581

4 ED67231310F1E1CD26BC793C,5D0

5 FEC020D0C900000000000000,377

FUENTE DE "PANTACA"

```
10          ORG  #9000
20          ENT  $
30 ADAPT:   LD   HL, #C00B
40          XOR  A
50 BUCLE1:  LD   C, A
60          AND  #07
70          LD   D, A
80          LD   A, C
90          RLCA
100         RLCA
110         AND  #E0
120         LD   E, A
130         LD   A, C
140         RRCA
150         RRCA
160         RRCA
170         AND  #1B
180         OR   D
190         OR   #40
200         LD   D, A
210         LD   B, #20
220         PUSH HL
230 BUCLE2: LD   A, (DE)
240         PUSH AF
250         AND  #F0
260         LD   (HL), A
270         INC  HL
280         POP  AF
290         LD   (HL), 0
300         RRD
310         INC  HL
320         INC  DE
330         DJNZ BUCLE2
340         POP  HL
350 CALL #BC26; SCR NEXT LINE
360         LD   A, C
370         INC  A
380         CP   #C0
390         JR   NZ, BUCLE1
400         RET
```

