

```
10 ' Headerless File Loader
20 ' By Jim 27/8/1988
30 MEMORY &A61F:addr=&A620
40 READ a$:IF a$="END" THEN 60 ELSE POKE addr,VAL("&" + a$):addr=addr+1
50 GOTO 40
60 MODE 2
70 PRINT "** Headerless File Loader **"
80 PRINT:INPUT "Enter start address :",ad
90 INPUT "Enter length of data :",lng
100 INPUT "Enter sync code :",cd
110 CALL &A620,cd,ad,lng
120 END
130 DATA FE,03,C0,DD,7E,00,DD,6E,02,DD
140 DATA 66,03,DD,5E,04,DD,56,05,CD,A1
150 DATA BC,D8,3E,07,C3,5A,BB,00,00,00
160 DATA END
```