

PROGRAMA CARGADOR

```
10 REM * CARGADOR CURSO C/M 21 *
20 REM ****
30 FOR N=&A000 TO &A034
40 READ A:SUMA=SUMA+A
50 POKE N,A
60 NEXT
70 IF SUMA<>&1472 THEN PRINT "ERROR
  EN DATAS"
80 DATA 42,50,160,205,26,188,58
90 DATA 49,160,71,197,229,6,8
100 DATA 197,229,84,93,126,245,35
110 DATA 58,48,160,6,0,79,237
120 DATA 176,241,18,225,17,0,8
130 DATA 25,193,16,231,225,17,80
140 DATA 0,25,193,16,219,201,50
150 DATA 2,5,5,0,0,0,0
```

PROGRAMA ENSAMBLADOR

1	ORG #A000	15	PUSH HL	28	LD DE, 2048
2		16	LD D, H	29	ADD HL, DE
3		17	LD E, L	30	POP BC
4	;CURSO DE CODIGO MAQUINA 21	18	LD A, (HL)	31	DJNZ BUC
5		19	PUSH AF	32	POP HL
6		20	INC HL	33	LD DE, 80
7	LD HL, (POSIC)	21	LD A, (ANCHO)	34	ADD HL, DE
8	CALL #BC1A	22	LD B, 0	35	POP BC
9	LD A, (LINEA)	23	LD C, A	36	DJNZ BUC1
10	LD B, A	24	LDIR	37	RET
11	BUC1: PUSH BC	25	POP AF	38	ANCHO: DEFB 50
12	PUSH HL	26	LD (DE), A	39	LINEA: DEFB 2
13	LD B, 8	27	POP HL	40	POSIC: DEFW #0505
14	BUC: PUSH BC				