

```

3 REM *****
4 REM *   PROGRAMME POUR SINCLAIR ZX SPECTRUM *
5 REM *****
10 CLS:LET M=0:LET P=0:LET R=0:OUT 255,3
20 PRINT AT 5,0:"QUEL MODE DE FONCTIONNEMENT DESIREZ VOUS:"
30 PRINT AT 10,5:"1: TEST PROPORTIONNEL"
40 PRINT AT 15,5:"2: COMMANDE DIRECTE"
50 PRINT AT 20,10:INPUT "VOTRE CHOIX ?".T
60 IF T<>1 AND T<>2 THEN GOTO 50
70 IF T=2 THEN GOTO 500
100 OUT 255,2
110 LET M=IN 255
120 OUT 255,1
130 LET P=IN 255
140 GOSUB 1000
300 OUT 255,R+2
310 LET M=IN 255
320 OUT 255,R+1
330 LET P=IN 255
340 GOTO 140
500 CLS
510 PRINT AT 10,5: INPUT "POSITION A ATEINDRE?".P
520 IF P<0 OR P>255 THEN GOTO 510
530 GOSUB 1000
540 OUT 255,R+2
550 LET M=IN 255
560 GOTO 530
1000 IF M>P THEN GOTO 1100
1010 IF M<P-20 THEN LET R=32
1020 IF M>P-20 AND M<P THEN LET R=160
1030 IF M=P OR M=P-1 THEN LET R=0
1100 IF M<P THEN GOTO 1200
1110 IF M>P-20 THEN LET R=64
1120 IF M<P-20 AND M>P THEN LET R=192
1130 IF M=P OR M=P+1 THEN LET R=0
1200 RETURN

```

```

3 REM *****
4 REM *   PROGRAMME POUR THOMSON MO S   *
5 REM *****
10 CLS:POKE 43006,3
20 LOCATE 1,5:PRINT "DUEL MODE DE FONCTIONNEMENT DESIREZ VOUS:"
30 LOCATE 5,10:PRINT "1: TEST PROPORTIONNEL"
40 LOCATE 5,15:PRINT "2: COMMANDE DIRECTE"
50 LOCATE 10,20:INPUT "VOTRE CHOIX ? ",T
60 IF T<>1 AND T<>2 THEN GOTO 50
70 IF T=2 THEN GOTO 500
100 POKE 43006,2
110 M=PEEK (43007)
120 POKE 43006,1
130 P=PEEK (43007)
140 GOSUB 1000
300 POKE 43006,R+2
310 M=PEEK (43007)
320 POKE 43006,R+1
330 P=PEEK (43007)
340 GOTO 140
500 CLS
510 LOCATE 5,10: INPUT "POSITION A ATEINDRE?",P
520 IF P<0 OR P>255 THEN GOTO 510
530 GOSUB 1000
540 POKE 43006,R+2
550 M=PEEK (43007)
560 GOTO 530
1000 IF M>P THEN GOTO 1100
1010 IF M<P-20 THEN LET R=32
1020 IF M>P-20 AND M<P THEN LET R=160
1030 IF M=P OR M=P-1 THEN LET R=0
1100 IF M<P THEN GOTO 1200
1110 IF M>P-20 THEN LET R=64
1120 IF M<P-20 AND M>P THEN LET R=192
1130 IF M=P OR M=P+1 THEN LET R=0
1200 RETURN

```